

**INSTALLATION PROCEDURES**

**FOR SINGLE CIRCUIT TRACK**

All track sections have an easy-to-see, embossed polarity line (Figure 1)  
 Fixtures have indicator arrows designed to point to the track polarity line (Figure 2)  
 To install:

1. Insert the fixture contacts into the track channel
2. Retract the track latch by gently pulling down
3. Rotate the adapter 90° so that the polarity arrow points to the polarity line on the track (Figure 3)

When the fixture is installed, the track latch will lock the fixture into the track  
**NOTE:** All latches should face the same direction after installation  
 Once fixture is installed into the track, move the ON/OFF switch to the "ON" position

**FOR TWO-CIRCUIT TRACK**

Fixtures have two contacts in the connector that engage conductors within the track; one for neutral and the other for the positive (live) conductor. Two circuit tracks contain one neutral and two positive conductors.

**To engage the second live conductor (Figure 4):**

1. Identify the "POSITIVE" connections on the lighting fixture base, marked "P".
2. To access the second circuit, pull up the connector marked "P" to the position shown.
3. Slide the plastic shim (shipped with track) beneath the connector, locking the tabs in place.

**To install the track fixture onto Two-Circuit Track:**

All track sections have an easy-to-see, embossed polarity line (Figure 1)  
 Fixtures have indicator arrows designed to point to the track polarity line (Figure 2)  
 To install:

1. Insert the fixture contacts into the track channel
2. Retract the track latch by gently pulling down
3. Rotate adapter 90° so that the polarity arrow points to the polarity line on the track (Figure 3)

When the fixture is installed, the track latch will lock the fixture into the track  
**NOTE:** All latches should face the same direction after installation  
 Once fixture is installed into the track, move the ON/OFF switch to the "ON" position

**DRIVER REPLACEMENT**

1. Open housing using Phillips screwdriver
2. Disconnect input and output wiring from existing driver
3. Connect input and output wiring to new driver
4. Close and secure fixture housing

**IMPORTANT SAFETY INSTRUCTIONS:**

- Read all the instructions before installation. Save instructions for later use.
- Turn off power at fuse or circuit breaker box before installation or any maintenance work.
- Wear rubber soled shoes and work on a sturdy wooden or non-conductive ladder.
- Product must be mounted in locations and at heights in compliance with National Electrical Code and local building codes. For indoor use only.
- Do not exceed the nominal supply voltage or amperage ratings.
- Installing contrary to instructions may cause unsafe conditions.
- **Warning:** Risk of fire. Most dwellings built before 1985 have supply wire rated at 60°C. Consult a qualified electrician before installation.
- Avoid hazards to children, account for all parts and properly dispose of all packing materials.
- Call the Technical Support department at ConTech Lighting with any installation questions: 847.559.5500.

**WARRANTY**

Energy Star products are covered for three (3) years by a full replacement guarantee after date of installation.  
 In addition, ConTech LED products carry a five (5) year limited warranty from date of purchase.

*All specifications subject to change without notice.*

